



1 Zone



1~10 Zone

AH-00212 Fire Alarm Control Panel

Characteristics

- This unit has Accumulation function, it can minimize the false alarm that caused by unstable pulse or any abnormal signal (false alarm) and no effect on the function of fire alarm at all.
- Each zone uses two different LED to indicate Fire alarm and Disconnection.
- Zone test switch uses single-loop press type to improve the twisting switch that its contact failure will caused by dust and improper use.
- Logical switch is different from traditional switch that needs to switch over higher voltage directly, it can prevent the damage caused by unstable voltage.
- External indicator power-save device can select Light ON or OFF under normal condition during power-off status, and stay blinking during alarm status which extend the operation life of control panel. (Prevent the control panel loss its function by wear-off on battery under power-off period)
- Easy to switch from fire alarm to smoke evacuation, sprinkling or foam system.
- Movable zone indication labels, they can be easily changed without affect its magnificent appearance.
- Annunciator is available on model AH-02124.

Specifications

Model	AH-00212 (1~10 zone)	AH-00212 (1 zone)
Power	220V AC/50Hz *Others also available	
Battery Capacity	24V DC 1.2Ah	24V DC 0.8Ah
Charging Voltage, Current	26V DC 100~400mA *With auto adjustment function	
Exterior Resistance	Round-trip under 50Ω	
# of heat detectors connected	No limit *Except electronic-type	
# of smoke detectors connected	30/zone *Horing Lih manufactured	
Max. Output Current	1A	500mA
End of Line Resistor	10kΩ *One per zone	
Material	1.2mm steel plate	
Color	Ivory white *Others also available	
Dimensions	350mm (H) x 285mm (W) x 105mm (D)	280mm (H) x 160mm (W) x 70mm (D)



AH-02124 Annunciator