



位置碼設置

定址探測器配線說明



撥至“ON”時表示“1”
撥至數字時表示“0”



測試方法
1. V^+ $2s^+$ $3v^-/s^-$
為訊號線，
測試時不可由此3條線路
短路動作，否則會造成總機
產生故障狀況

2. $4, 5$
為固定感知器的觸片
測試時，可直接將兩點
短路，動作訊號則會傳
回總機，即可完成測試
動作條件

編碼	指撥方式	編碼	指撥方式	編碼	指撥方式				
01	10000000	51	11001100	101	10100110				
02	01000000	52	00101100	102	01100110				
03	11000000	53	10101100	103	11100110				
04	00100000	54	01101100	104	00010110				
05	10100000	55	11101100	105	10010110				
06	01100000	56	00011100	106	01010110				
07	11100000	57	10011100	107	11010110				
08	00010000	58	01011100	108	00110110				
09	10010000	59	11011100	109	10110110				
10	01010000	60	00111100	110	01110110				
11	11010000	61	10111100	111	11110110				
12	00110000	62	01111100	112	00001110				
13	10110000	63	11111100	113	10001110				
14	01110000	64	00000010	114	01001110				
15	11110000	65	10000010	115	11001110				
16	00001000	66	01000010	116	00101110				
17	10001000	67	11000010	117	10101110				
18	01001000	68	00100010	118	01101110				
19	11001000	69	10100010	119	11101110				
20	00101000	70	01100010	120	00011110				
21	10101000	71	11100010	121	10011110				
22	01101000	72	00010010	122	01011110				
23	11101000	73	10010010	123	11011110				
24	00011000	74	01010010	124	00111110				
25	10011000	75	11010010	125	10111110				
26	01011000	76	00110010	126	01111110				
27	11011000	77	10110010	127	11111110				
28	00111000	78	01110010						
29	10111000	79	11110010						
30	01111000	80	00001010						
31	11111000	81	10001010						
32	00000100	82	01001010						
33	10000100	83	11001010						
34	01000100	84	00101010						
35	11000100	85	10101010						
36	00100100	86	01101010						
37	10100100	87	11101010						
38	01100100	88	00011010						
39	11100100	89	10011010						
40	00010100	90	01011010						
41	10010100	91	11011010						
42	01010100	92	00111010						
43	11010100	93	10111010						
44	00110100	94	01111010						
45	10110100	95	11111010						
46	01110100	96	00000110						
47	11110100	97	10000110						
48	00001100	98	01000110						
49	10001100	99	11000110						
50	01001100	100	00100110						